



Dear New Kiva DSL customer,

Thank you for choosing Kiva Networking as your high speed Internet service provider. You will be notified by phone as to when your DSL service will begin working and given your username and password at that time. Please notify us immediately if you have any trouble with your self-install kit. Your billing will begin on the same day that your DSL service starts unless you notify us that you are having problems. If you have questions or need help during your self-install then please call our Technical Support Department and we'll be happy to answer your questions and help you finish your install.

If you have any other questions or need further assistance, please feel free to contact Technical Support at the phone number below or e-mail us.

Thank You

Technical Support/Customer Services--Kiva Networking
e-mail: help@kiva.net--voice: 337-5070 or 800-819-8143



Kiva Networking DSL Information sheet

This information will be provided over the phone from Kiva Networking

PPPOE username: _____@kiva.net

Password: _____

Kiva username: _____

Technical Support
help@kiva.net
337-5070
800-819-8143

Trouble shooting tips

1. Restart the DSL modem, wait for the DSL light to go solid green.
2. Restart the router (if present), wait 1-2 minutes.
3. Restart the computer.

Please Save this Information

Kiva Networking DSL Self-install directions

Directions for the AT&T High Speed Internet modem

Open the package containing the DSL modem

The package should contain

1 DSL modem and power Supply

Multiple DSL line filters

AT&T software CD

1 DSL telephone cable

1 Ethernet Data cable

The DSL telephone cable and the Ethernet data cable are very similar but the Ethernet data cable has slightly larger ends that will not fit into a telephone jack.

Set AT&T software CD to the side (Do not use the AT&T Software)

Install a line filter on each phone and device (Satellite TV, Alarm, fax machine, etc.) that uses a phone line by

Unplugging the phone line from the telephone wall jack,

Plugging the DSL line filter into the telephone wall jack,

Plugging the phone line into phone side of the DSL line filter.

The DSL modem will need to be plugged into a telephone wall jack near the computer.

If the DSL modem and a phone will share a wall jack then plug the DSL telephone cable into the DSL opening of the line filter otherwise plug the DSL telephone cable directly into the telephone wall jack.

Plug the other end of the DSL phone cable into the DSL port on the DSL modem

Plug one end of the Ethernet Data cable into the Ethernet port on the computer

Plug the other end of the Ethernet Data Cable into the Ethernet port on the DSL modem

Plug the round end of the power cable into the DSL modem's power port

Plug the power cable into surge protector or wall socket

Turn on the DSL modem (the switch is in back on the left side)

The power light should go from red to green within one minute

The DSL light should go from Flashing red to Flashing green to solid green

The Ethernet light should be off

Turn on the computer

The Ethernet light should turn on and be solid green

Open a web browser (Internet Explorer, Netscape, Firefox, etc.)

In the address bar type 192.168.0.1 (for the Speedstream modem)

In the address bar type 192.168.1.254 (for the Motorola modem)

The Modem Login page should load.

Enter your Kiva Networking PPPOE Username (given to you by the eGIX technician) in the User ID: block
Enter your Kiva Networking password (given to you by the eGIX technician) in the Password: block
Click on the Connect button
Click on the Connection Information button on the left side.

The IP address line should show a 216.9.142.??? or 216.9.143.??? IP address. If the IP address shows then you are connected.

Close the web browser window and reopen the window.
Your home page should appear.
You are now connected

If you have any other questions or need further assistance, please feel free to contact Technical Support at the phone number below or e-mail us.

Thank You

Technical Support/Customer Services--Kiva Networking
e-mail: help@kiva.net--voice: 337-5070 or 800-819-8143
